Coherency Tuning via Phase Conjugation in Fiber Laser Networks.

A.Yu.Okulov*
Russian Academy of Sciences, 119991, Moscow, Russian Federation.
(Dated: December 20, 2014)

Phase-locking of large mode area Yb photonic crystal fiber amplifiers via stimulated Brillouin scattering phase conjugation is analyzed. The wavefront reversing mirrors are proposed for chirped pulse fiber laser networks. The chirp control via both nonresonant Kerr and resonant index is considered.

PACS numbers: 42.65.Hw,42.65.Jx,42.65.Re,42.55.Wd,42.60.Jf

arXiv:1412.6696v2 [physics.optics] 26 Dec 2014

The networks of fiber lasers with kilohertz repetition rates promise a revolutionary characteristics of particle accelerators and high energy density facilities [1, 2]. For this purpose a lattice of the fiber amplifiers emitting a thousands of beamlets of mJ pulses with identical chirped spectrum could maintain a high spatial and temporal coherency under accurate ($\lambda/10$ - $\lambda/20$) tuning of optical paths [3].

The equalization of optical paths difference ΔL in laser sets might be achieved by means of phase conjugation (PC) as well [4, 5]. This wavefront reserving technique when backwardly amplified wave $\mathbf{E_b}$ propagates as *time reversal* replica of incident wave $\mathbf{E_f}$ provides a unique opportunity for coherency protection in fiber amplifier sets [6]. When phase-conjugated mirrors with Stimulated Brillouin scattering are used the phase lag $\Delta\phi = \Delta k \Delta L$ due to gigahertz frequency difference between incident and PC reflected wave $\Delta k = k_f - k_b$ may be effectively used for decoupling of master oscillator and amplifier set [7] when $\Delta\phi = \pi$. In this robust PC interferometry the amplifier set is automatically self-adjusted even for the low quality optical components [8].

In addition to recent proposal of chirped pulse PC mirrors with instantaneous $Kerr$ response [6] via degenerate four-wave mixing ($DFWM$) one may suggest the fiber amplifier set (fig.1) with Brillouin enhanced four-wave mixing PCM [9] in order to improve the PC reflectivity and stability with respect variations of $DFWM$ PCM beams. The duration of master oscillator is taken to avoid random phase jumps uniformly distributed within interval $[-\pi, \pi]$ of PC reflected SBS wave [10] . In this scheme the transform limited (i.e. nonchirped) envelope laser pulse of nanosecond duration $\tau \sim 1\ nsec$ is injected into binary tree Michelson amplifier set and backwardly reflected from Brillouin PCM [11]. Because τ is significantly smaller than acoustical phonon lifetime τ_{ph} [12] the acoustical grating in PCM is $frozen$ during reflection [13]. Thus temporal envelope of reflected wave will be identical to the incident one:

$$E_{PC}(z,t,\vec{r}) = f(z \pm ct)\mathbf{E_f}^*(z,\vec{r})$$
$$\cong f(z \pm ct)\sum_{m,n} a^*_{m,n}(z,\vec{r}) \cdot \exp\,[-i\Delta\Phi_{m,n}], \quad (1)$$

where $f(z \pm ct)$ is $transform\ limited$ temporal envelope of the master oscillator pulse, $\mathbf{E_f}(z,\vec{r}) = \sum a_{m,n}(z,\vec{r}) \cdot \exp\,[i\Delta\Phi_{m,n}]$ is spatial slowly varying envelope, $\Delta\Phi_{m,n}$ are phase piston errors compensated due to SBS PCM. The phase piston errors are responsible for decoherence of laser arrays [14] and filamention of the single lobe far field pattern [15].

The mechanism of high fidelity of PCM reflection is in propagation of Stockes component inside randomly spaced helical waveguides forming speckle pattern [16]. The helicity of SBS speckle phase conjugated pattern [17] is due to alternation of the orbital angular of light in phase conjugation [18, 19] and excitation of acoustical vortices carrying orbital angular momentum [20].

In order to realize the basic advantages of chirped pulse compression technique [21] the chirping frequency modulation might be produced via combined action of χ^3 nonresonant Kerr index $f(z+ct)\exp[ikn_2 \ln|f(z+ct)|^2]$ and modulation via resonant index of Yb ions changes due to backward propagation in saturated fiber amplifier (fig.1). The chirped self phase modulation of backwardly amplified wave $\mathbf{E_b}$ is described by nonlinear Shrodinger-Frantz-Nodvik

*Electronic address: alexey.okulov@gmail.com; URL: http://okulov-official.narod.ru

equation [22]:

$$\frac{\partial \mathbf{E_b}(z,t,\vec{r})}{\partial z} - \frac{n_r}{c}\frac{\partial \mathbf{E_b}}{\partial t} + \frac{i}{2k_b}\nabla_{\perp}^{2}\mathbf{E_b} = \frac{\sigma_{_{Yb}}\, N(z,t)}{2}\mathbf{E_b}(1 + i\Delta\omega T_2) + ikn_2|\mathbf{E_b}|^2 \cdot \mathbf{E_b}, \tag{2}$$

with dynamics of population inversion $N(z,t)$ given by:

$$\frac{\partial N(z,t)}{\partial t} = -\sigma_{_{Yb}} N(z,t) \cdot |\mathbf{E_b}|^2 + \frac{N_0(z) - N(z,t)}{T_1}, \tag{3}$$

where $\sigma_{_{Yb}} \sim 10^{-20} cm^2$ is stimulated cross section of Yb^{3+} resonant transition, T_1, T_2 are longitudinal and transversal relaxation times of Yb ions, $\Delta\omega$ is detuning of carrier frequency of $\mathbf{E_b}$ from the center of gain line of Yb ions.

The exact solution taking into account gain saturation of the nonlinear Shrodinger-Frantz-Nodvic may be obtained in explicit form because for $\tau \sim 10^{-9}$ *sec* and for the typical distance between of fiber amplifiers set and PCM $> 15cm$ the backward wave $\mathbf{E_b}$ is amplified without interference with forward wave $\mathbf{E_f}$ [6]:

$$\mathbf{E_b}(z,t) = \frac{\mathbf{E_b}(z=0,t) \cdot exp\left[-ikn_2 \int_0^{L_f} [|\mathbf{E_b}(\eta,t)|^2 - i\Delta\omega T_2 \sigma T_1 |\mathbf{E_b}(\eta,t)|^2] d\eta\right]}{\sqrt{1 - [1 - exp\left[-\sigma_{_{Yb}} \int_0^{L_f} N_0(z')dz'\right] exp\left[\, -2\sigma_{_{Yb}} \int_{-\infty}^{t-z/v_g} |\mathbf{E_b}(z,\tau)|^2 d\tau\right]}}, \tag{4}$$

where L_f is average length of fiber amplifier. The solution (4) was obtained using procedure described in [23] is valid for short ($L_f \sim 2m$) large mode area mJ-level fiber amplifier [24]. The figure of merit (FOM) of phase-locked single spatial mode output is evaluated [6].

[1] G. Mourou, B. Brocklesby, T. Tajima and J. Limpert, "The future is fibre accelerators", Nature Photonics, **7**, 258 (2013).
[2] G.A.Mourou, T.Tajima and S.V.Bulanov, "Optics in the relativistic regime", Rev.Mod.Phys., **78**, 309 (2006).
[3] J.Bourderionnet,C.Bellanger, J. Primot and A. Brignon "Collective coherent phase combining of 64 fibers", Opt. Express **19(18)**, 17053-17058 (2011).
[4] Robert A. Fisher, "Optical Phase Conjugation", Academic,(1983).
[5] A.Brignon (Ed.), "Coherent Laser Beam Combining", Wiley, 498 pp. September (2013).
[6] A.Yu.Okulov, "Coherent chirped pulse laser network with Mickelson phase conjugator", Appl. Opt. , **53**, 2302 (2014).
[7] N.G.Basov, I.G.Zubarev, A.B.Mironov, S.I.Mikhailov and A.Yu.Okulov, "Laser interferometer with wavefront reversing mirrors ", JETP, **52**, 847 (1980).
[8] D. A. Rockwell and C.R. Giuliano, "Coherent coupling of laser gain media using phase conjugation", Opt. Lett, **11**, 147 (1986).
[9] M.W. Bowers and R. W. Boyd, "Phase Locking via Brillouin-Enhanced Four-Wave-Mixing Phase Conjugation", IEEE Journ.Quantum Electronics, **34**, 634-644 (1998).
[10] N.G.Basov, I.G.Zubarev, A.B.Mironov, S.I.Mikhailov and A.Yu.Okulov, "Phase fluctuations of the Stockes wave produced as a result of stimulated scattering of light", JETP Lett, **31**, 645 (1980).
[11] N.G.Basov, I.G.Zubarev, A.B.Mironov, S.I.Mikhailov and A.Yu.Okulov, "Laser system", Patent of the USSR N 1088620 (Author's certificate), published 22 December 1983, filed October 23 (1980).
[12] I.G.Zubarev, A.B.Mironov, S.I.Mikhailov and A.Yu.Okulov, "Accuracy of reproduction of time structure of the exciting radiation in stimulated scattering of light", JETP, **57**, 270 (1983).
[13] R.W.Boyd, *"Nonlinear Optics"*,(Academic Press, 3ed.),(2007).
[14] A.Yu.Okulov,"The effect of roughness of optical elements on the transverse structure of a light field in a nonlinear Talbot cavity", J.Mod.Opt. **38**, n.10, 1887 (1991).
[15] A.Yu.Okulov,"Scaling of diode-array-pumped solid-state lasers via self-imaging", Opt.Comm., **99**, p.350-354 (1993).
[16] A.Yu.Okulov, "Twisted speckle entities inside wavefront reversal mirrors", Phys.Rev.A , **80**, 013837 (2009).
[17] M.Woerdemann, C.Alpmann and C.Denz, "Self-pumped phase conjugation of light beams carrying orbital angular momentum", Opt. Express, **17**, 22791(2009).
[18] A.Yu.Okulov,"Angular momentum of photons and phase conjugation", J.Phys.B., **41**, 101001 (2008).
[19] A.Yu.Okulov, "Phase-conjugation of the isolated optical vortex using a flat surfaces", J. Opt. Soc. Am. B **29**, 714-718 (2012).
[20] A.Yu.Okulov, "Optical and Sound Helical structures in a Mandelstam - Brillouin mirror", JETP Lett., **88**, 631 (2008).
[21] D. Strickland and G. Mourou, "Compression of amplified chirped optical pulses", Opt. Commun. **56**,219-221 (1985).
[22] A.Yu.Okulov, A.N.Oraevsky, "Compensation of self-focusing distortions in quasiresonant amplification of a light pulse", Sov.J.Quant.Elect.,**18**, 233 (1988).



FIG. 1: Michelson binary tree for coherent summation of **Yb** fiber amplifiers lattice. **BS** are 50/50 beamsplitters, M are mirrors, $\Delta k \Delta L = \pi$ is output decoupling phase lag due to **SBS PCM** reflection [7], **SBS PCM** is broad area lightguide SBS four wave mixing enhanced mirror [9] with speckle pattern produced by **Yb** fiber amplifiers set , the spectrum colors with imposed envelope show the **PCM** reflected pulses whose chirp is induced by backward propagation in resonant gain medium [22]. **SBS PCM reference** is mirror for reference waves E_{ref_f} E_{ref_b}.

[23] R.V.Ambartsumyan, N.G.Basov, V.S.Zuev, P.G.Kryukov, V.S.Letokhov, "Nonlinear amplification of light pulses", JETP, **23**,16 (1966).

[24] T. Eidam, J. Rothhardt, F. Stutzki, F. Jansen, S. Hadrich, H. Carstens, C. Jauregui, J. Limpert, and A. Tunnermann, "Fiber chirped-pulse amplification system emitting 3.8 GW peak power", Opt. Express **19(1)**,255-260 (2011).